

## **FIXED SPEED VORTEXER MIXER SPECIFICATIONS**

---

<b>Overall dimensions (L x W x H):</b>	7 x 4.4 x 5.3" (17.8 x 11.2 x 13.5 cm)
<b>Electrical (50/60 Hz):</b>	120V: 1.2 amps, 135 watts 230V: 0.6 amps, 135 watts
<b>Speed range:</b>	120V: 3200rpm 230V: 2500rpm
<b>Orbit:</b>	4.9mm (0.194")
<b>Duty rating:</b>	intermittent duty
<b>Controls:</b>	none
<b>Ship weight:</b>	10lbs (4.5kg)

## **ANALOG VORTEXER MIXER SPECIFICATIONS**

---

<b>Overall dimensions (L x W x H):</b>	7 x 4.4 x 5.3" (17.8 x 11.2 x 13.5 cm)
<b>Electrical (50/60 Hz):</b>	120V: 1.2 amps, 135 watts 230V: 0.6 amps, 135 watts
<b>Speed range*:</b>	120V: 300 to 3200rpm 230V: 300 to 2500rpm
<b>Orbit:</b>	4.9mm (0.194")
<b>Duty rating:</b>	intermittent duty
<b>Controls:</b>	auto/off/on rocker switch, speed knob: variable 1 to 10 dial marks
<b>Ship weight:</b>	10lbs (4.5kg)

## **DIGITAL VORTEXER MIXER SPECIFICATIONS**

---

<b>Overall dimensions (L x W x H):</b>	7 x 4.4 x 5.3" (17.8 x 11.2 x 13.5 cm)
<b>Electrical (50/60 Hz):</b>	120V: 1.2 amps, 135 watts 230V: 0.6 amps, 135 watts
<b>Speed range*:</b>	120V: 500 to 3000rpm 230V: 500 to 2500rpm
<b>Timer:</b>	1 second to 9999 minutes
<b>Orbit:</b>	4.9mm (0.194")
<b>Duty rating:</b>	intermittent duty
<b>Controls:</b>	see page 5
<b>Ship weight:</b>	10lbs (4.5kg)

## **PULSING VORTEXER MIXER SPECIFICATIONS**

---

<b>Overall dimensions (L x W x H):</b>	7 x 4.4 x 5.3" (17.8 x 11.2 x 13.5 cm)
<b>Electrical (50/60 Hz):</b>	120V: 1.2 amps, 135 watts 230V: 0.6 amps, 135 watts
<b>Speed range*:</b>	120V: 500 to 3000rpm 230V: 500 to 2500rpm
<b>Timer:</b>	1 second to 9999 minutes
<b>Orbit:</b>	2.5mm (0.098")
<b>Duty rating:</b>	intermittent duty
<b>Controls:</b>	see page 5
<b>Ship weight:</b>	10lbs (4.5kg)

\* Maximum speed will vary depending on accessory being used.